

32/16 CHANNELS

16 PROGRAMMABLE SCENES

2 PROGRAMMABLE CHASES

DMX-512 OPTION

RUGGED

PORTABLE



This console provides versatility with simple operation. It is portable and very rugged. It has the ability to link with another TL-3216 or a TL-1608 to provide increased channel capacity. "BUMP" buttons give instant-on capability. The chase rate is user controlled and both chases can be run together to provide complex patterns. Other features include a Master fader, split cross faders, and blackout control.

SPECIFICATIONS

Channels:	32 or 16	Control Protocol:	3 pin LMX-128 (multiplex) Optional DMX-512
Operating Modes:	16 Channels X 2 Scenes 32 Channels X 1 Scene 16 Channels + 16 Scenes	Power Requirements:	13 - 25 vdc or vac 600 milliamps
Chase:	2 X 23 steps each User programmable	Size:(inches)	15.25w x 8.25h x 2.25d
Scene Memory:	16 scenes 32 channels each	Weight:	4 lbs